

**YAMAHA**



**MIDI EXPANDER**

OWNER'S MANUAL


# **YAMAHA**

# **YME8**

Thank you for purchasing the Yamaha YME8 MIDI (Musical Instrument Digital Interface) Expander. The YME8 is a parallel box designed especially for Digital Interfacing. In order to gain the proper performance from this unit, be sure to read this instruction booklet thoroughly before using it.

# CAUTION

---

- If for some reason you should use any other AC adapter than the one provided with the YME8 (the PA-1), be sure it is the following type: DC6 — 12V, +  —. Special care must be taken that adapters of reverse polarity are not used.
- When finished using the YME8, do not forget to put both selector switches at OFF, and make sure the red indicator turns off.
- Do not use this unit near a window where the unit may be exposed to direct sunlight, or in any other extremely hot locations, as this may impair its performance.
- Take good care of the unit; be careful not to drop it or treat it roughly in any way.
- Irreparable damage may result from opening the YME8 cabinet or attempting to alter the internal circuitry. If there is a problem, contact your nearest Yamaha dealer.

# SPECIFICATIONS


---

MIDI IN	: 2
MIDI THRU	: 2 lines of 4
Selector Switches	: Input Selectors (2)
Power	: External DC 6 - 12V 100mA
Dimensions	: 164mm x 30mm x 72mm
(W x H x D)	(6-1/2" x 1-1/8" x 2-7/8")
Weight	: 503g (1.1 lbs.)
Accessory	: AC Adapter (PA-1)

# USAGE

☆ Use the selector switches to choose the desired combination of input.

EXAMPLE 1) With this set up, the keyboard/sequencer connected to MIDI IN 1 will control all eight keyboards connected to the MIDI THRU.



**EXAMPLE 2)** With this set up, the keyboard/sequencer connected to MIDI IN 1 controls the keyboards connected to MIDI THRU 1 to 4. And, the keyboard/sequencer connected to MIDI IN 2 controls the keyboards connected to MIDI THRU 5 to 8.

